

KRK V SERIES - 2 POWERED MONITORS

PRECISION: Introducing KRK's V Series 2 powered studio monitors – precision speakers designed to forever change the way you handle your most demanding jobs.

V SERIES 2 monitors are hallmarked by defined low end, articulate midrange and precise highs, delivering clarity and accuracy on par with many world-class speakers costing far more.

In addition, V Series 2 monitors feature several key design elements that have made the KRK sound a "studio standard". These include radiused edges for improved imaging and slotted ports that greatly reduce distortion caused by port turbulence. What's more, we've included some valuable and practical enhancements like a speaker protection circuit for added confidence, an auto-on/off feature for improved convenience and upgraded driver and amplifier components to ensure peak performance in even the most demanding professional environments.

Whether you are making critical mixing decisions or capturing the subtle nuance of a unique sound, you'll quickly discover that the V Series 2 monitors are as precise about your work as you are.

SPECIFICATIONS

V4 Series 2

- Video Shielded
- HF 1" Soft Dome Tweeter
- LF 4" Kevlar Woofer
- XLR - 1/4" TRS Combo
- Auto On / Off
- Clip Indicator / Limiter Switch
- Amplification: HF15 W, LF 30 W
- 12dB/octave filters
- Freq Response: 62Hz - 20kHz
- Max SPL: Music: 102dB, Peak: 106dB

V6 Series 2

- Video Shielded
- HF 1" Soft Dome Tweeter
- LF 6" Kevlar Woofer
- XLR - 1/4" TRS Combo
- Auto On / Off
- Clip Indicator / Limiter Switch
- Amplification: HF30 W, LF 60 W
- 24dB/octave filters
- Freq Response: 55Hz - 20kHz
- Max SPL: Music: 106dB, Peak: 109dB

V8 Series 2

- Video Shielded
- HF 1" Soft Dome Tweeter
- LF 8" Kevlar Woofer
- XLR - 1/4" TRS Combo
- Auto On / Off
- Clip Indicator / Limiter Switch
- HF & LF Adjustments
- Amplification: HF 60 W, LF 120 W
- 24dB/octave filters
- Freq Response: 42Hz - 20kHz
- Max SPL: Music: 109dB, Peak: 111dB

V12 S

- 12" High Excursion Kevlar Woofer
- XLR Inputs and Outputs
- 200 Watt High Current Amplifier
- Subwoofer Level Adjust
- Phase Switch 0° - 180°
- Fixed 80Hz High Pass Line Outputs
- Auto On / Off
- Clip Indicator / Limiter Switch
- Remote Foot Switch
- Freq Response: 29 Hz-50 Hz to 130 Hz



KRK Systems, L.L.C.

9340 De Soto Ave., • Chatsworth, California 91311

Phone: 1-818-534-1580 • Fax: 1-818-534-1581 • www.krksys.com

